



445

Second generation powerful all-round saw for people who value professional qualities in a saw. Starts easily also with a slower pull, comes with flip-up tank caps. The X-Torq® engine means lower fuel consumption and reduced emission levels. Auto return stop switch and visible fuel level makes the saw easier to handle. Equipped with Smart Start® and fuel pump to every time ensure easy starts.



FLIP-UP TANK CAP

The flip-up tank cap is easy to open and close when refueling.



SMART START®

The engine and starter have been designed so the machine starts quickly with minimum effort. Resistance in the starter cord is reduced by up to 40%.



FUEL PUMP

Fuel pump designed for easy starting.



INERTIA CHAIN BRAKE

Effective inertia-activated chain brake.

Features

- Less filter cleanings with Air Injection
- X-Torq® engine cuts emission and fuel consumption
- Easy to start
- Quick-release air filter
- Felling marks for correct felling direction
- Intuitive, combined choke/stop control
- Quick and easy chain adjustment
- Easy to maintain with snap locked cylinder cover
- Maximum durability for tough applications
- LowVib® sparing the user's arms and hands
- Fuel level window
- Easy to start

Technical data

Cylinder displacement	45.7 cm ³ / 2.8 cu.inch
Power output	2.1 kW
Maximum power speed	9000 rpm
Fuel tank volume	0.45 lit / 15.22 fl oz
Fuel consumption	481 g/kWh
Idling speed	2700 rpm
Spark plug	Champion RCJ7Y, NGK BPMR7A
Electrode gap	0.5 mm / 0.02 "
Torque, max.	2.4 Nm/6300 rpm
Oil tank volume	0.26 lit / 0.55 US pint
Oil pump type	Fixed flow
Equivalent vibration level (ahv, eq) front / rear handle	1.9/2.6 m/s ²
Sound pressure level at operators ear	103 dB(A)
Sound power level, guaranteed (LWA)	114 dB(A)
Chain pitch	.325"
Recommended bar length, min-max	33-50 cm / 13"-20"
Chain speed at max power	17.3 m/s / 56.76 fts
Weight (excl. cutting equipment)	4.9 kg / 10.8 lbs

ARTICLES

967 15 64-38	18" - .325 - SN - H30 - Europe	€ 579.99
--------------	--------------------------------	----------

